

# KVV-65A-3XKIT



Tri-sector solution that includes 3 KVV-65A-R2-V1 antennas and mounting kit to install them on a pipe

- Suitable for attachment to 3.5-6.6 in or 89-168 mm outer diameter pipe
- Compatible with canister concealment shrouds with inner diameter > 23.5 in (597mm)
- Minimum shroud diameter is the same for all applicable pipe diameters

## General Specifications

<b>Band</b>	Multiband
<b>Performance Note</b>	Outdoor usage
<b>RF Connector Interface</b>	4.3-10 Female
<b>RF Connector Location</b>	Bottom
<b>RF Connector Quantity, mid band</b>	12
<b>RF Connector Quantity, low band</b>	6
<b>RF Connector Quantity, total</b>	18

## Electrical Specifications

<b>Operating Frequency Band</b>	1695 – 2690 MHz   617 – 960 MHz
---------------------------------	---------------------------------

## Packaging and Weights

<b>Width, packed</b>	601 mm   23.661 in
<b>Depth, packed</b>	1027 mm   40.433 in
<b>Length, packed</b>	1667 mm   65.63 in
<b>Weight, gross</b>	128.8 kg   283.955 lb

## Regulatory Compliance/Certifications

<b>Agency</b>	<b>Classification</b>
UK-ROHS	Compliant

## \* Footnotes

<b>Performance Note</b>	Severe environmental conditions may degrade optimum performance
-------------------------	---