H9MB-602

6-1/8 in EIA Male Flange with gas barrier for 5 in HJ9-50 air dielectric cable

OBSOLETE

This product was discontinued on: April 1, 2014

Product Classification

Product Type Air coaxial connector

Product Brand HELIAX®

General Specifications

Body Style Straight
Cable Family HJ9-50
Gas Barrier Yes

Inner Contact Attachment Method Thread-in stub

Inner Contact Plating Silver

Interface 6-1/8 in EIA Male Flange

Mounting AngleStraightOuter Contact Attachment MethodTab-flareOuter Contact PlatingUnplated

Dimensions

Length 241.3 mm | 9.5 in

Diameter 206.248 mm | 8.12 in

Nominal Size 5 in

Electrical Specifications

Insertion Loss, typical 0.05 dB

Average Power at Frequency 57.0 kW @ 900 MHz

Cable Impedance50 ohmConnector Impedance50 ohmdc Test Voltage28 kV

Insulation Resistance, minimum 5000 MOhm



H9MB-602

Operating Frequency Band 0 - 860 MHz
Peak Power, maximum 1890 kW

RF Operating Voltage, maximum (vrms) 9721 V

VSWR/Return Loss

Frequency Band	VSWR	Return Loss (dB)
45-500 MHz	1.03	39.3
510-1000 MHz	1.03	39.3
1010-1500 MHz	1.03	39
1510-2200 MHz	1.03	38.6
2210-2500 MHz	1.04	35

Environmental Specifications

Operating Temperature $-40 \,^{\circ}\text{C}$ to $+150 \,^{\circ}\text{C}$ (-40 $^{\circ}\text{F}$ to $+302 \,^{\circ}\text{F}$)

Storage Temperature $-70 \,^{\circ}\text{C}$ to $+100 \,^{\circ}\text{C}$ (-94 $^{\circ}\text{F}$ to $+212 \,^{\circ}\text{F}$)

Packaging and Weights

Weight, net 16.78 kg | 36.994 lb

Regulatory Compliance/Certifications

Agency Classification

ISO 9001:2015 Designed, manufactured and/or distributed under this quality management system



* Footnotes

Insertion Loss, typical 0.05v⁻freq (GHz) (not applicable for elliptical waveguide)

