NG4-VSMRF28 | NG4 VAM, 2 1X8 SPLITTERS, LC /APC, RIGHT



NG4access® Module VAM, Splitter, 1x8, symmetrical split, singlemode, LC /APC, front, right, 2 circuits

- VAMs help enhance optical transport systems by providing flexible, easy to incorporate optical components into the network
- VAMs increase fiber capacity and help troubleshooting or distributing signals to multiple subscribers

Product Classification

Regional Availability

Asia | Australia/New Zealand | China | EMEA | India | Latin

America | North America

PortfolioCommScope®Product TypeSplitter moduleProduct BrandNG4access®Product SeriesFACT | NG4

General Specifications

Device Type Plug-and-play module

Functionality Splitting

Technology Type Planar lightwave circuit (PLC)

Access Front

Application For use with NG4 access frames

Distribution Type 1 x 8 splitter (2)

 Interface, front
 LC/APC

 Interface, Input
 LC/APC

 Interface, Output
 LC/APC

Split Ratio Symmetrical

Splitter, quantity 2

Tray Orientation Right orientation

Dimensions

 Height
 13.21 mm | 0.52 in

 Width
 159.77 mm | 6.29 in

COMMSCOPE®

NG4-VSMRF28 | NG4 VAM, 2 1X8 SPLITTERS, LC /APC, RIGHT

Depth 130.3 mm | 5.13 in

Optical Specifications

Directivity, minimum 55 dB

Performance Grade Grade O (PLC, low loss)

Polarization Dependent Loss, maximum 0.2 dB Uniformity, maximum 1.4 dB

Wavelength Range 1260–1625 nm

Insertion Loss, Splitter, maximum10.8 dBReturn Loss, Connector, minimum55 dB

Packaging and Weights

Packaging quantity 1

